



# Switch to Advance Plastic-Sign Ballasts Today!

## SLI/Power Lighting/Valmont to ADVANCE Sign Ballast Cross Reference

SLI / Power Lighting / Valmont Part No.	Number of Lamps	Lamp Feet	Case Type	Alternate Part Number	ADVANCE Part No.	No. of Lamps	Lamp Feet	Case Type	Comments
6G3753AWF	5-6	10-25	D	V56L10-25	ASB-1240-46-BL-TP	4-6	12-40	BL3	For most, 2.5" Longer
6G3780AWF	3	18-24	C		ASB-1224-24-BL-TP	2-4	12-24	BL2	Same size
6G3782WF	2-4	20-28	C	V234L20-28	ASB-2040-24-BL-TP	2-4	20-40	BL3	4.8" Longer
6G3784WF	3-4	24-32	D	V34L24-32	ASB-2040-24-BL-TP	2-4	20-40	BL3	2.5" Longer
6G3787AWF	4-6	24-36	E	V456L24-36	ASB-1240-46-BL-TP	4-6	12-40	BL3	Same size
6G3804WF	2-4	16-24	C		ASB-1224-24-BL-TP	2-4	12-24	BL2	Same size
6G3809WF	3	12-18	B		ASB-0620-24-BL-TP	2-4	6-20	BL1	Same size
6G3814WF	2-4	8-16	B	V234L8-16	ASB-0620-24-BL-TP	2-4	6-20	BL1	Same size
6G3901WF	1-2	4-12	B	V12L4-12	ASB-0412-12-BL-TP	1-2	4-12	BL1	Same size
6G3909WF	1	2-4	A	V1L2-4	NA				
6G3932WF	1-2	3-6	A	V12L3-6	ASB-0412-12-BL-TP	1-2	4-12	BL1	For most, 0.8" Taller
6G3940WF	2-4	4-8	B	V234L4-8	Check application				"0412" or "0620" for some
6G3942AW	4-6	32-48	F	V456L32-48	ASB-2448-46-BL-TP	4-6	24-48	BL3	4.6" Shorter
6G3951WF	3	6-12	B		ASB-0620-24-BL-TP	2-4	6-20	BL1	Same size
6G3959WF	2-4	16-24	C	V234L16-24	ASB-1224-24-BL-TP	2-4	12-24	BL2	Same size
6G4041WF	4-6	24-36	D		ASB-1240-46-BL-TP	4-6	12-40	BL3	2.5" Longer
6G4100WD	2-4	14-24	G		ASB-1224-24-BL-TP	2-4	12-24	BL2	4.8" Shorter, smaller H&W
6G4102WD	2-4	6-12	G		ASB-0620-24-BL-TP	2-4	6-20	BL1	7.4" Shorter, smaller H&W
6G4104WD	4	24-32	G		ASB-1240-46-BL-TP	4-6	12-40	BL3	Smaller H&W
V12L3-6	1-2	3-6	A	6G3932WF	ASB-0412-12-BL-TP	1-2	4-12	BL1	For most, 0.8" Taller
V12L4-12	1-2	4-12	B	6G3901WF	ASB-0412-12-BL-TP	1-2	4-12	BL1	Same size
V1L2-4	1	2-4	A	6G3909WF	NA				
V234L16-24	2-4	16-24	C	6G3959WF	ASB-1224-24-BL-TP	2-4	12-24	BL2	Same size
V234L20-28	2-4	20-28	C	6G3782WF	ASB-2040-24-BL-TP	2-4	20-40	BL3	4.8" Longer
V234L4-8	2-4	4-8	B	6G3940WF	Check application				"0412" or "0620" for some
V234L8-16	2-4	8-16	B	6G3814WF	ASB-0620-24-BL-TP	2-4	6-20	BL1	Same size
V34L24-32	3-4	24-32	D	6G3784WF	ASB-2040-24-BL-TP	2-4	20-40	BL3	2.5" Longer
V456L24-36	4-6	24-36	E	6G3787AWF	ASB-1240-46-BL-TP	4-6	12-40	BL3	Same size
V456L32-48	4-6	32-48	F	6G3942AW	ASB-2448-46-BL-TP	4-6	24-48	BL3	4.6" Shorter
V56L10-25	5-6	10-25	D	6G3753AWF	ASB-1240-46-BL-TP	4-6	12-40	BL3	For most, 2.5" Longer



# Advance Sign Ballasts -

for T12/HO Rapid Start Fluorescent Lamps

## SLI/Power Lighting/Valmont to ADVANCE Sign Ballast Cross Reference

ADVANCE Part No.	Black	White	Blue	Red	Yellow	Blue / White	Brown	Orange	Orange / Black	Case Type
ASB-0412-12-BL-TP	18	18	33	33	51					BL1
ASB-0620-24-BL-TP	24	24	75	46	75	46	46			BL1
ASB-1224-24-BL-TP	24	24	74	32	70	52	78			BL2
ASB-1240-46-BL-TP	24	24	50	80	70	50	50	50	50	BL3
ASB-2040-24-BL-TP	24	24	80	80	72	54	72			BL3
ASB-2448-46-BL-TP	24	24	50	50	70	50	50	50	50	BL3

ADVANCE - Ballast Enclosure Dimensions				
ADVANCE Case Type	Length (in.)	Width (in.)	Height (in.)	Mounting Length (in.)
BL1	11.750	3.187	2.625	11.141
BL2	14.312	3.187	2.625	13.750
BL3	19.187	3.187	2.687	18.625

SLI - Ballast Enclosure Dimensions				
SLI Case Type	Length (in.)	Width (in.)	Height (in.)	Mounting Length (in.)
A	11.750	3.125	1.781	11.141
B	11.750	3.125	2.625	11.141
C	14.312	3.125	2.625	13.750
D	16.687	3.125	2.625	16.125
E	19.187	3.125	2.625	18.625
F	23.812	3.125	2.750	23.0
G	19.187	3.750	3.562	18.625

Specifications subject to change without notice.  
 Printed in U.S.A. © 2001 Advance Transformer Co.  
**Form No. MA-3000-AA-R01**



Advance Transformer Co. • O'Hare International Center  
 10275 West Higgins Road • Rosemont, Illinois 60018  
 Telephone: (800) 322-2086 • FAX: (888) 423-1882  
 Customer Support/Technical Service: (800) 372-3331  
[www.advancetransformer.com](http://www.advancetransformer.com)

A DIVISION OF PHILIPS ELECTRONICS NORTH AMERICA CORPORATION